



# EMC<sup>®</sup> Storage Monitoring and Reporting

Version 4.0

## Upgrading to ViPR SRM

P/N 302-002-733

REV 03

**EMC<sup>2</sup>**

Copyright © 2016 EMC Corporation. All rights reserved. Published in the USA.

Published September 2016

EMC believes the information in this publication is accurate as of its publication date. The information is subject to change without notice.

The information in this publication is provided as is. EMC Corporation makes no representations or warranties of any kind with respect to the information in this publication, and specifically disclaims implied warranties of merchantability or fitness for a particular purpose. Use, copying, and distribution of any EMC software described in this publication requires an applicable software license.

EMC<sup>2</sup>, EMC, and the EMC logo are registered trademarks or trademarks of EMC Corporation in the United States and other countries. All other trademarks used herein are the property of their respective owners.

For the most up-to-date regulatory document for your product line, go to EMC Online Support (<https://support.emc.com>).

EMC Corporation  
Hopkinton, Massachusetts 01748-9103  
1-508-435-1000 In North America 1-866-464-7381  
[www.EMC.com](http://www.EMC.com)

# CONTENTS

<b>Chapter 1</b>	<b>Upgrading the System</b>	<b>5</b>
	Overview.....	6
	Required credentials.....	6
	Verifying and documenting the current status of the environment.....	6
	Backing up the environment.....	6
	Upgrading to ViPR SRM.....	7
<b>Chapter 2</b>	<b>Post-Upgrade Tasks</b>	<b>9</b>
	Validating the environment.....	10

## CONTENTS

# CHAPTER 1

## Upgrading the System

This chapter includes the following topics:

- [Overview](#)..... 6
- [Required credentials](#)..... 6
- [Verifying and documenting the current status of the environment](#).....6
- [Backing up the environment](#).....6
- [Upgrading to ViPR SRM](#).....7

## Overview

When you upgrade Storage Monitoring and Reporting to ViPR SRM, the upgrade process removes the frontend modules of the Storage Monitoring and Reporting instance and reuses the backed and collector in the ViPR SRM instance.

---

### Note

Storage Monitoring and Reporting and ViPR SRM must be running the same version.

---

## Required credentials

Gather the necessary credentials.

- Administrator credentials for Storage Monitoring and Reporting.
- Web Service Gateway credentials for ViPR SRM.

## Verifying and documenting the current status of the environment

Verify and document the current status of the environment before starting the upgrade process. This will help you evaluate the success of the upgrade.

### Before you begin

Refer to chapter 4 of the *ViPR SRM Administrator's Guide* for details about verifying the health of your system.

Refer to the *ViPR SRM Performance and Scalability Guidelines* for details about determining configuration size.

---

### Note

If you install ViPR SRM in a different location than Storage Monitoring and Reporting, your deployment must still meet the network latency limits described in the guidelines.

---

### Procedure

1. Look for blank reports and graphs. Determine if there are any blank reports caused by collection errors. Resolve any issues or document them for later follow up.
2. Look for broken links and resolve any issues or document them for later follow up.
3. Validate that topology is working. Resolve any issues.

### After you finish

Engage EMC Support to resolve any observed issues prior to proceeding with the upgrade.

## Backing up the environment

Ensure the proper backup of all of the servers in your environment. This includes all of the frontend, backend, and collector hosts.

Before starting the upgrade, use Discovery Center to export all of your SolutionPack devices.

If it is allowed in your environment, perform a complete shutdown of ViPR SRM and Storage Monitoring and Reporting and take an offline VMware snapshot of each VM

before starting the upgrade. These snapshots will allow you to quickly recover if you encounter any problems during the upgrade. After the upgrade is complete without any errors, you can delete these snapshots.

If a VMware snapshot of each VM is not allowed, you should completely power cycle the vApps and/or VMs before starting the upgrade.

#### Note

Notify all users not to log in during the upgrade.

Refer to the following guides for details about your backup system:

- *EMC ViPR SRM: Backing Up with VMware vSphere Data Protection Advanced 5.8*
- *EMC ViPR SRM: vApp Backup and Restore Using EMC Networker*
- *EMC ViPR SRM: Backing up with EMC Avamar 7.1*
- *EMC ViPR SRM: vApp Backup and Restore Using IBM Tivoli Storage Manager*
- *EMC ViPR SRM: vApp Backup and Restore Using Symantec NetBackup*
- *EMC ViPR SRM: vApp Backup and Restore using Commvault Simpana Virtual Server Protection*

These guides are available from the [ViPR SRM Product Documentation Index](#).

## Upgrading to ViPR SRM

### Before you begin

- Storage Monitoring and Reporting and ViPR SRM must be the same version.
- ViPR SRM and Storage Monitoring and Reporting must both be running.
- For Storage Monitoring and Reporting for Unity, the same version of the SolutionPack for EMC VNX must be installed in ViPR SRM. Refer to the *ViPR SRM SolutionPack Installation Guide*.
- For Storage Monitoring and Reporting for VPLEX, the same version of the SolutionPack for EMC VPLEX must be installed in ViPR SRM. Refer to the *ViPR SRM SolutionPack Installation Guide*.
- There should not be any system related health alerts in the EMC M&R Health reports in ViPR SRM or Storage Monitoring and Reporting

### Procedure

1. On the Storage Monitoring and Reporting instance, enter the following URL:  
`http://<Frontend-hostname>:58080/upgrade`
2. In the **Authentication** section, enter the Storage Monitoring and Reporting username and password. The default username is **admin**, and the default password is **changeme**.
3. In the **Hostname** field of the **SRM installation** section, enter the FQDN of the ViPR SRM frontend server.
4. Enter the ViPR SRM username and password. The default username is **admin**, and the default password is **changeme**.
5. Click **Connect**.

The system validates the installation.

6. Click **Next**.
  7. Click **Complete Installation**.
- 

**Note**

You can safely ignore any messages about "Moving alerting contexts."

8. Close the Upgrader window.
9. Log in to ViPR SRM at <http://<Frontend-hostname>:58080/APG>.



# CHAPTER 2

## Post-Upgrade Tasks

This chapter includes the following topics:

- [Validating the environment](#)..... 10

## Validating the environment

After upgrading your system, verify the operational status.

---

### Note

After upgrading to ViPR SRM, do not install new SolutionPacks on the Storage Monitoring and Reporting host.

---

### Note

You can discover new devices on the Storage Monitoring and Reporting host. For example, if you upgraded from Storage Monitoring and Reporting for VPLEX, you can discover additional VPLEX arrays. However, before you add the new devices, ensure that they will not cause the system to exceed the collector limits described in the Storage Monitoring and Reporting performance and scalability guidelines.

---

### Procedure

1. Verify that the upgraded Storage Monitoring and Reporting host is listed under **Centralized Management** > **Physical Overview** as a new node.
2. Verify that all services have started on the upgraded Storage Monitoring and Reporting host:
  - a. In **Centralized Management** > **Physical Overview**, click the host name.
  - b. Verify that the status for each service is Started.
  - c. If a service did not start automatically, click the name of the service, and then click **Start**.
3. Navigate to **Discovery Center** > **Devices Management** and verify that the devices that existed in Storage Monitoring and Reporting before the upgrade are listed in ViPR SRM.
4. Look for blank reports and graphs.

Determine whether blank reports are caused by collection errors. Resolve issues or document them for later follow up.
5. Look for broken links. Resolve issues or document them for later follow up.
6. Verify that all tasks are completing successfully (with the possible exception of automatic updates and ESRS).
7. Validate that topology is working. Resolve any issues.
8. Verify or edit polling periods.